ourdiu.com | Shared by Abrar Hasan Chowdhury

Daffodil International University

Faculty of Science & Information Technology
Department of Computer Science & Engineering
Final Examination, Summer 2025
Course Code: CSE331, Course Title: Compiler Design
Level: 3 Term: 3 Batch: 62

Time: 02:00 Hrs. **Marks: 40**

Answer ALL Questions

[The figures in the right margin indicate the full marks and corresponding course outcomes. All portions of each question must be answered sequentially.]

1.	*a)*	Consider the following grammar to produce LR(0) parser and Canonical Table. **E → E+E | E*E | (E) | id**	[8]	CO2

	b)	`int main() {`
		`  int a = 10, b=2;`
		`  int c = a + b;`
		`  int f = a + b;`
		`  int i = f;`
		`  while (i < 20) {`
		`  int temp2 = a * b;`
		`  i++;`
		`  }`
		`  if (c < 0) { i = e + f; }`
		`  return temp2+i ;`
		`}`
		Relate the optimization techniques that can be applied to the above code. Rewrite the code after applying optimization techniques.
			[2]	

2.	*a)*	Suppose you are part of a compiler design team assigned to develop a predictive parser for a basic arithmetic expression grammar. The grammar is defined as: **E→ E+T | E-T | T T→T*F | T/F | F F→ (E) | id** Apply analytical skills to: i. **Eliminate left recursion** from the given grammar and write the equivalent grammar suitable for predictive parsing. ii. Develop the **predictive parsing table** for the modified grammar iii. When can a grammar be called an **LL(1) grammar**?	[2] [6] [2]	CO2
3.	*a)*	Consider the following expression and answer the questions. **speed + distance * (rate + fee) - (limit * speed) + gain / (extra + fee) + distance * limit** i. Represent the expression using Three Address Code (TAC). ii. Represent the expression using Quadruples. iii. Implement a Triples data structure to represent the expression.	[6]	CO3
	b)	Using 3(a) equation answer the following questions.	[4]	

ourdiu.com | Shared by Abrar Hasan Chowdhury

		i. Construct the Syntax Tree for the expression. ii. Construct a Directed Acyclic Graph (DAG) for the expression.		
4.	*a)*		[6]	CO3

1	t89 = b[t42]	16	if t17 > t52 goto (22)
2	goto (22)	17	t3 = t40 / t65
3	a[t82] = t59	18	if t42 < t5 goto (11)
4	b[t16] = t89	19	goto (46)
5	if t29 >= t98 goto (16)	20	if t17 >= z goto (22)
6	t96 = a[t66]	21	t89 = a[t52]
7	m = t15	22	t38 = c[t13]
8	t77 = a[t3]	23	v = t67
9	c[t53] = t16	24	if t44 >= t2 goto (26)
10	z = t12	25	x = t35
11	j = t52	26	if t14 < t69 goto (19)
12	j = t72	27	b[t57] = y
13	goto (42)	28	x = t63
14	if t22 == t34 goto (36)	29	t82 = b[t54]
15	t90 = b[t53]	30	v = t40

i. Which lines in the code qualify as leaders by leader selection rule 2?
ii. Is / Are there any instruction(s) designated as leaders more than twice?
iii. Conclude the total number of basic blocks identified from the code?

	b)	Draw the **flow graph** for the above mentioned instructions.	[4]